

Amendments To The Claims

The listing of claims presented below will replace all prior versions and listings of claims in the application.

Listing of claims:

1. **(currently amended)** An apparatus for generating random numbers using digital logic, comprising:

a shift register which sequentially moves bit values stored therein;

a feedback circuit which performs a **first** predetermined logic operation on the bit values stored in the shift register to generate a feedback signal;

an external signal generation circuit which generates an external signal input to the shift register; and

an input logic circuit which performs a **second** predetermined logic operation on the feedback signal and the external signal and inputs a result of operation to the shift register; and

a fixed value prevention circuit that generates a signal with a value that allows an output of the input logic circuit to have a different value to a value of an output of the shift register and inputs the generated signal to the input logic circuit, when a logic value of the external signal is equivalent to all the bit values stored in the shift register, **and**

wherein the external signal is directly connected to the input logic circuit.

2. **(canceled).**

3. (original) The apparatus of claim 2, wherein the signal output from the fixed value

prevention circuit is at logic high.

4. (original) The apparatus of claim 1, wherein the external signal generation circuit generates a random signal.

5. (original) The apparatus of claim 4, wherein the random signal is generated by sampling a sampled signal generated by a source that is different from a source of a sampling signal.

6. (original) The apparatus of claim 5, wherein sampling is performed both at rising and falling edges of the sampling signal generated by a source that is different from a source of the sampled signal.

7. **(currently amended)** A method of generating random numbers using digital logic, comprising:

- (a) sequentially moving bit values stored in a shift register;
- (b) performing a predetermined logic operation on the bit values stored in the shift register to generate a feedback signal;
- (c) generating an external signal input to the shift register; and
- (d) performing a predetermined operation on the feedback signal and the external signal and inputting a result of the operation to the shift register, **and**
wherein the predetermined logic operation is further performed on an

output of a fixed value prevention circuit that allows the result of the
predetermined logic operation to be different to the bit values of the shift register,
when a logic value of the external signal is equivalent to all the bit values stored
in the shift register, and
wherein the external signal and the output of the fixed value prevention
circuit are directly inputted into the predetermined logic operation.

8. (canceled).
9. (original) The method of claim 8, wherein the output of the fixed value prevention circuit is at logic high.
10. (original) The method of claim 7, wherein the external signal is a random signal.
11. (original) The method of claim 10, wherein the random signal is generated by sampling a sampled signal generated by a source that is different from a source of a sampling signal
12. (original) The method of claim 11, wherein sampling is performed both at rising and falling edges of the sampling signal generated by a source that is different from a source of the sampled signal.